

CHUKA



UNIVERSITY

UNIVERSITY EXAMINATIONS

**EXAMINATION FOR THE AWARD OF BACHELOR OF SCIENCE IN ELECTRICAL
AND ELECTRONIC ENGINEERING**

EENG 464: POWER GENERATION**STREAMS: BSc. EENG****TIME: 2 HOURS****DAY/DATE: TUESDAY 19/12/2023****8.30 A.M. – 10.30 A.M.****INSTRUCTIONS**

- Answer question ONE and any other TWO questions
- Do not write on the question paper

QUESTION ONE (30 MARKS)

- a) Discuss the factors that need to be taken into account while selecting the site for a hydro power station. (4 Marks)
- b) A steam power station has an overall efficiency of 25% and 0.8 kg of coal is burnt per kWh of electrical energy generated. Calculate the calorific value of fuel. (3 Marks)
- c) A thermal station has the following data : Max. demand = 20,000 kW ; Load factor = 40%
Boiler efficiency = 85% ; Turbine efficiency = 90% Coal consumption = 0.9 kg/kWh ; Cost of 1 ton of coal = Ksh.450
Determine
- i). thermal efficiency (1 Marks)
 - ii). Coal bill per annum. (2 Marks)
- d) Outline the advantages of Solar Power plants over steam power plants. (2 Marks)
- e) What is the power output of a $^{92}\text{U} 235$ reactor if it takes 30 days to use up 2 kg of fuel?
Given that energy released per fission is 200 MeV and Avogadro's number = 6.023×10^{26} per kilomole. (4 Marks)

- f) Wind at a speed of 10 meters per second passed through a wind turbine with a blade radius of 20m. What is the theoretical power available and the maximum fraction of power available? (3 Marks)
- g)
- i). Briefly explain the working principle a fuel cell (2 Marks)
 - ii). Highlight the application of fuel cells (2 Marks)
- h) Water for a hydro-electric station is obtained from a reservoir with a head of 100 metres. Calculate the electrical energy generated per hour per cubic metre of water if thehydraulic efficiency be 0.86 and electrical efficiency 0.92. (4 Marks)
- i) Describe the different types of fuel cell technologies. (3 Marks)

QUESTION TWO (20 MARKS)

- a) A steam power station spends Ksh.4.5 Million per annum for coal used in the station. The coal has a calorific value of 5000 kcal/kg and costs Ksh.450 per ton. If the station has thermal efficiency of 33% and electrical efficiency of 90%, find the average load on the station. (5 Marks)
- b) Describe the schematic arrangement of a MHD power station. Briefly explain the functions of the components. (5 Marks)
- c) Discuss the merits and demerits of Nuclear Power Plants. (4 Marks)
- d) The following data for a 2200 kW diesel power station was given .The peak load on the plant is 1600 kw and its load factor is 45% .Capacity cost/kw installed =Ksh.15000, Annual costs=15% of capital , Annual Maintenance cost=Fixed Ksh.100000 and a Variable cost Ksh.200000 , annual operating cost=Ksh.600000 , Cost of Fuel=Ksh.0.8 per kg,cost of lubricating oil=Ksh.40 per kg, C.V of Fuel=40000 kj/kg , consumption of fuel =0.5kg/kwh , Consumption of Lubricating oil=1/400 kg/kwh. Determine:
- i). The annual energy produced
 - ii). Cost of generation per kwh
 - iii). Efficiency (6 Marks)

QUESTION THREE (20 MARKS)

- a) Highlight the functions of a Surge tank in hydroelectric in hydroelectric power plant design. (2 Marks)

- b) A hydro-electric power station has a reservoir of area 2.4 square kilometres and capacity $5 \times 10^6 \text{ m}^3$. The effective head of water is 100 metres. The penstock, turbine and generation efficiencies are respectively 95% , 90% and 85% .
- (i) Calculate the total electrical energy that can be generated from the power station. (3 Marks)
- (ii) If a load of $15,000 \text{ kW}$ has been supplied for 3 hours, find the fall in reservoir level (5 Marks)
- c) Describe Three hydroelectric Power plant classifications (3 Marks)
- d) The weekly discharge of a typical hydroelectric plant is as under :

Day	Sun	Mon	Tue	Wed	Thu	Fri	Sat
Discharge (m ³ /sec)	500	520	850	800	875	900	546

The plant has an effective head of 15 m and an overall efficiency of 85% . If the plant operates on 40% load factor, estimate

- (i) the average daily discharge (1 Marks)
- (ii) pondage required (3 Marks)
- (iii) installed capacity of proposed plant. (3Marks)

QUESTION FOUR (20 MARKS)

- a) Define the following terms used in Solar Energy generation.
- i). Insolation (1Marks)
- ii). Irradiaton (1Marks)
- b) Consider a 100-cm^2 photovoltaic cell with reverse saturation current $I_0 = 10^{-12} \text{ A/cm}^2$. In full sun, it produces a shortcircuit current of 40 mA/cm^2 at 25°C .
- i). Find the open-circuit voltage at full sun and again for 50% sunlight. (4 Marks)
- ii). Plot I-V graph of the photovoltaic cell. (3Marks)
- iii). From I-V graph explain the I_{sc} and V_{oc} variation with Sunlight Intensity. (3 Marks)
- c) Describe the working Principle of an Hydroelectric Power Plant using diagrams and illustrations. (5 Marks)
- d) Outline THREE drawbacks of Thermal Power Plants. (3 Marks)

.....